



Digital bone conducted spectacles

Product Information

The AN-Evo1 is a digital bone conducted spectacle, suitable for mild to moderate hearing losses. The opportunities of individual programming by the fitting software BHMFit2 or standard adjusting with N - H trimmer, permit a maximum of flexibility in meeting the individual needs.

BHM bone conduction hearing systems - a reliable solution without the risk of surgery!

Accessories

BHM bone conduction hearing temples can be integrated into a variety of attractive spectacles-fronts. BHM also offers the possibility to mount onto any appropriate spectacles.

Features

- Battery size 675
- 10 channel digital amplifier with programming options over 4 pin programming socket
- Low cut trimmer (N H)
- O-T-M switch
- Temple in different colours
- Temple Version for Coselgi® available*

Additional features using the fitting software BHMFit2 and the HI-PRO box:


- Graphic equalizer
- MPO limiting (AGC0)
- Activate/Deactivate selection of volume control
- Activate/Deactivate selection of N H trimmer

^{*}By offering a separate version with special connecting interface even upgrading of Coselgi® spectacles with BHM hearing systems is enabled.



| Total harmonic distortion (pi = 70 dBSPL ref. test gain) | 500 Hz 800 Hz 1000 Hz 1600 Hz | < 1 % < 0.5 % < 0.5 % < 0.2 % |
|---|--|--|
| Equivalent input noise level | • | 26.0 dBSPL |
| Current consumption | | 1.2 mA ± 10 % |
| Battery life | | ~ 475 h @ 570 mAh |





C € According to EU guidelines 93/42/EEC Quality management system according to DIN EN ISO 13485







Digital bone conducted spectacles

Measured at $U_{\rm B} = 1.35 \text{ V}$

| Technical data Tolerance of acoustic values ± 4 dB | | IEC 118-9 IEC 60318-6 Artificial Mastoid |
|---|---|---|
| Supply Voltage | | 1.35 V |
| Maximum Output Force Level (OFL90) MPO = Min. | Max. 1000 Hz 1600 Hz | 117 dB0FL 112 dB0FL 111 dB0FL |
| Maximum Output Force Level (OFL90) MPO = Max | Max. 1000 Hz 1600 Hz | 97 dB0FL 90 dB0FL 90 dB0FL |
| Maximum Acousto-Mechanical Sensitivity Level | Max. 1000 Hz 1600 Hz | 48 dB 45 dB 41 dB |
| Sensitivity of telephone coil | ••••••••••••••••••••••••••••••••••••••• | typ. 90 dB (@ 10 mA/m, 1 kHz) |

